

DCounter™ Mini Indoor People Counter Specifications

Feature	PCM01S	PCM01D	PCS01x
Picture	 PCM01S	 PCM01D	 PCS01M PCS01ST
Brand	DCounter (PCM01S)	DCounter (PCM01D)	DCounter (PCM01D)
Detection Method	Single Modulated infrared sensors	Dual Modulated infrared sensors	Dual Modulated infrared sensors
Materials	PVC	PVC	Steel
Box Color	Black	Black	Black
Dimension	Sender Box : 8.5 x 10.7 x 3.5 cm Receiver Box : 8.5 x 10.7 x 3.5 cm	Sender Box : 8.5 x 10.7 x 3.5 cm Receiver Box : 8.5 x 10.7 x 3.5 cm	Sender Box : 15x10x90 cm Receiver Box : 15x10x90 cm
Counter Display	Characters LCD - Display Size: 65 x 14 mm - Font Size: 3.7 x 6.3 mm - Color: Yellow/Black , Blue/Blue	Characters LCD - Display Size: 65 x 14 mm - Font Size: 3.7 x 6.3 mm - Color: Yellow/Black , Blue/Blue	Characters LCD - Display Size: 65 x 14 mm - Font Size: 3.7 x 6.3 mm
Counter Max.	65535 People	65535 People	65535 People
Sensing Distance	4 Meters	2 Meters	2.5 Meters
Bi-Direction Counter		●	●

Power Supply	220 VAC 50Hz < 1Watt	220 VAC 50Hz < 1Watt	220 VAC 50Hz < 1Watt
Relay Outputs	●	●	(Optionanl)
Software Monitor & Reports		●	●
Data Protocols	N/A	RS232 , TCP/IP (Optional)	RS232 , TCP/IP (Optional)
Software Setting		●	●
MultiGate Support		●	●
Large Display Support			●
Build-in Memory	●	●	●
LEDs indicators	4 LEDs - 1 LEDs indicating status of Power On - 1 LEDs indicating reception status of each infrared detector - 2 LEDs indicating status of data communication	5 LEDs - 1 LEDs indicating status of Power On - 2 LEDs indicating reception status of each infrared detector - 2 LEDs indicating status of data communication	5 LEDs - 1 LEDs indicating status of Power On - 2 LEDs indicating reception status of each infrared detector - 2 LEDs indicating status of data communication
User Interface	<u>Receiver Box</u> 1 Slide Switch ON-OFF 1 Push Switch Reset 1 Connector Relay (NO,Com.,NC) 1 RS232 (DB9) 2 DC Jack <u>Sender Box</u> 1 DC Jack	<u>Receiver Box</u> 1 Slide Switch ON-OFF 1 Push Switch Reset 1 Connector Relay (NO,Com.,NC) 1 RS232 (DB9) 2 DC Jack <u>Sender Box</u> 1 DC Jack	<u>Receiver Box</u> 1 Slide Switch ON-OFF 1 Push Switch Reset 1 Connector Relay (NO,Com.,NC) 1 RS232 (DB9) 2 DC Jack <u>Sender Box</u> 1 DC Jack

Warranty	1 Year	1 Year	1 Year
----------	--------	--------	--------